

NUMBER	WORD	DESCRIPTION
0	OK	Command executed without error.
1	CONNECT	Carrier detected (300 or 1200 bps if X0 is set).
2	RING	Phone is ringing.
3	NO CARRIER	Carrier lost or never detected.
4	ERROR	Error in command line, line too long, or invalid character format.
5	CONNECT 1200	Connection at 1200 bps if X1 is set.
6	NO DIAL TONE	No dial tone is detected within 5 seconds and X2 or X4 is set.
7	BUSY	Busy signal is detected and X3 or X4 is set.
8	NO ANSWER	Displayed when "@" dial modifier used and phone continues to ring.
10	CONNECT 2400	Carrier detected at 2400 bps. X1 or X4 must be set.

NOTES:

- * V0 and V1 are the modem commands that determine whether the modem is to render numeric or verbal result codes, respectively.
- * The Q command determines whether or not results are sent.
- * Another command related to the result code is the X command. Depending on the selected value of this command, the result code that appears will vary.
- * RING only indicates that the phone is ringing. The modem does not answer unless it is commanded to or unless auto-answer is enabled.
- * NO CARRIER is displayed if the carrier signal from the other modem is not detected for a sufficient length of time. NO CARRIER means that a data call was not successfully completed.

(smm 07/28/93)