

STAKING PIN JUMPERS

Selecting a COM Port		Multi Line Business		Auto-Answer Operation	
CN4 * *	CN4 * *	CN3 * *	CN3 * *	CN7 * *	CN7 * *
Com 2 Setting (default)	Com 1 Setting	Multi- Line Use	Normal (default)	Auto answer	No Auto answer (default)

Selecting the Interrupt Signal		
Select Interrupt Signal	IRQ3 (default)	IRQ4
Shorting Connector Position	CN5    CN6 *    * *    *	CN5    CN6 *    * *    *

IMPORTANT

Tandy 1000 and 1000A (250-1000/A) with 25-1037, 2400 BPS Internal Modem

There is a modification needed to be made to the Tandy 1000 or 1000A in order for the 25-1037 modem to work. This modem requires a -5 volt connection through the card slot that the Tandy 1000 and 1000A do not have.

Without the modification to the 1000 the modem will pickup the telephone line, dial a number, but will not go any further. No connection is made and communication is not possible. The modification can be done by an authorized Radio Shack service center.

(smm 07/28/93)

(smc-09/14/93)